

# PRELIMINARY TECHNICAL DATA

## Zero-Drift, Single-Supply, Rail-to-Rail Input/Output Low Noise Operational Amplifier

# a

### Preliminary Technical Data

### AD8628

#### FEATURES

- Lowest auto-zero amplifier noise
- Low Offset Voltage: 5  $\mu\text{V}$
- Input Offset Drift: 0.03  $\mu\text{V}/^\circ\text{C}$
- Rail-to-Rail Input and Output Swing
- 5 V Single-Supply Operation
- High Gain, CMRR, and PSRR: 120 dB
- Very Low Input Bias Current: 100 pA
- Low Supply Current: 1.3 mA
- Overload Recovery Time: 0.2 ms
- No External Components Required

#### APPLICATIONS

- Automotive Sensors
- Pressure and Position Sensors
- Strain Gage Amplifiers
- Medical Instrumentation
- Thermocouple Amplifiers

#### GENERAL DESCRIPTION

This new family of amplifiers has ultra-low offset, drift and bias current. The AD8628 is a wide bandwidth auto-zero amplifier featuring rail-to-rail input and output swings and low noise. Operation is fully specified from 2.7 to 5 volts single supply ( $\pm 1.35\text{V}$  to  $\pm 2.5\text{V}$  dual supply).


The AD8628 family provides the benefits previously found only in expensive auto-zeroing or chopper-stabilized amplifiers. Using Analog Devices' new topology these zero-drift amplifiers combine low cost, with high accuracy and low noise. (No external capacitors are required.) In addition, the AD8628 greatly reduces the digital switching noise found in most chopper stabilized amplifiers.

With an offset voltage of only 1  $\mu\text{V}$ , drift less than 0.005  $\mu\text{V}/^\circ\text{C}$  and noise of only 0.5  $\mu\text{V}$  P-P (0Hz to 10 Hz) the AD8628 is perfectly suited for applications where error sources cannot be tolerated. Position and pressure sensors, medical equipment, and strain gage amplifiers benefit greatly from nearly zero drift over their operating temperature range. Many systems may take advantage of the rail-to-rail input and output swings provided by


the AD8628 family to reduce input biasing complexity and maximize SNR.

The AD8628 family is specified for the extended industrial ( $-40^\circ$  to  $+125^\circ\text{C}$ ) temperature range. The AD8628 amplifier is available in the tiny SOT23 and the popular 8-pin narrow SOIC plastic packages.

5-Lead SOT  
(RT-5)



8-Lead SO  
(R-8)



Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.  
Tel: 617/329-4700 World Wide Web Site: <http://www.analog.com>  
Fax: 617/326-8703 © Analog Devices, Inc., 2002

# PRELIMINARY TECHNICAL DATA

## AD8628

### ELECTRICAL SPECIFICATIONS (@ $V_S=+5.0V$ , $V_{CM} = +2.5V$ , $V_O=+2.5V$ , $T_A=+25^\circ C$ unless otherwise specified.)

Parameter	Symbol	Conditions	Min	Typ	Max	Units
<b>INPUT CHARACTERISTICS</b>						
Offset Voltage	$V_{OS}$	$-40^\circ C \leq T_A \leq +125^\circ C$		1	5	$\mu V$
Input Bias Current	$I_B$	$-40^\circ C \leq T_A \leq +125^\circ C$		30	100	$\mu A$
Input Offset Current	$I_{OS}$	$-40^\circ C \leq T_A \leq +125^\circ C$		50	200	$\mu A$
Input Voltage Range		$-40^\circ C \leq T_A \leq +125^\circ C$	0		5	V
Common-Mode Rejection Ratio	CMRR	$V_{CM} = 0V$ to $5V$ $-40^\circ C \leq T_A \leq +125^\circ C$	120	140		dB
Large Signal Voltage Gain (Note 1)	$A_{VO}$	$R_L = 10 k\Omega$ , $V_O=0.3$ to $4.7V$ $-40^\circ C \leq T_A \leq +125^\circ C$	125	145		dB
Offset Voltage Drift	$\Delta V_{OS}/\Delta T$	$-40^\circ C \leq T_A \leq +125^\circ C$		0.002	0.03	$\mu V/^\circ C$
<b>OUTPUT CHARACTERISTICS</b>						
Output Voltage High	$V_{OH}$	$R_L = 100k\Omega$ to Ground $-40^\circ C \leq T_A \leq +125^\circ C$	4.99	4.996		V
		$R_L = 10k\Omega$ to Ground $-40^\circ C \leq T_A \leq +125^\circ C$	4.95	4.98		V
Output Voltage Low	$V_{OL}$	$R_L = 100k\Omega$ to $V+$ $-40^\circ C \leq T_A \leq +125^\circ C$		1	10	mV
		$R_L = 10k\Omega$ to $V+$ $-40^\circ C \leq T_A \leq +125^\circ C$		2	10	mV
Short Circuit Limit	$I_{SC}$	$-40^\circ C \leq T_A \leq +125^\circ C$	$\pm 25$	$\pm 50$	20	mV
Output Current	$I_O$	$-40^\circ C \leq T_A \leq +125^\circ C$		$\pm 30$		mV
		$-40^\circ C \leq T_A \leq +125^\circ C$		$\pm 15$		mV
<b>POWER SUPPLY</b>						
Power Supply Rejection Ratio	PSRR	$V_S = 2.7V$ to $5.5V$ $-40^\circ C \leq T_A \leq +125^\circ C$	120	130		dB
Supply Current/Amplifier	$I_{SY}$	$V_O = 0V$ $-40^\circ C \leq T_A \leq +125^\circ C$	115	130	1.5	dB
				1.3	1.8	mV
				1.6		mV
<b>DYNAMIC PERFORMANCE</b>						
Slew Rate	SR	$R_L = 10 k\Omega$		0.8		V/ $\mu s$
Overload Recovery Time				0.05	0.2	ms
Gain Bandwidth Product	GBP			2.5		MHz
<b>NOISE PERFORMANCE</b>						
Voltage Noise	$e_{n p-p}$	0.1 to 10 Hz		0.5		$\mu V_{p-p}$
Voltage Noise	$e_{n p-p}$	0.1 to 1.0 Hz		0.16		$\mu V_{p-p}$
Voltage Noise Density	$e_n$	$f = 1 kHz$		22		nV/ $\sqrt{Hz}$
Current Noise Density	$i_n$	$f=10 Hz$		5		fA/ $\sqrt{Hz}$

Note 1: Gain testing is highly dependent upon test bandwidth.

# PRELIMINARY TECHNICAL DATA

## AD8628

### ELECTRICAL SPECIFICATIONS (@ $V_S=+2.7V$ , $V_{CM} = +1.35 V$ , $V_O=1.4V$ , $T_A=+25^\circ C$ unless otherwise specified.)

Parameter	Symbol	Conditions	Min	Typ	Max	Units
<b>INPUT CHARACTERISTICS</b>						
Offset Voltage	$V_{OS}$	$-40^\circ C \leq T_A \leq +125^\circ C$		1	5	$\mu V$
Input Bias Current	$I_B$	$-40^\circ C \leq T_A \leq +125^\circ C$		30	100	pA
Input Offset Current	$I_{OS}$	$-40^\circ C \leq T_A \leq +125^\circ C$		1.0	1.5	nA
Input Voltage Range		$-40^\circ C \leq T_A \leq +125^\circ C$		50	200	pA
Common-Mode Rejection Ratio	CMRR	$V_{CM} = 0$ to 2.9V $-40^\circ C \leq T_A \leq +125^\circ C$	0 115	130	5	V dB
Large Signal Voltage Gain	$A_{VO}$	$R_L = 10 k\Omega$ , $V_O=0.3$ to 4.7V $-40^\circ C \leq T_A \leq +125^\circ C$	110	140		dB
Offset Voltage Drift	$\Delta V_{OS}/\Delta T$	$-40^\circ C \leq T_A \leq +125^\circ C$		105	130	dB
<b>OUTPUT CHARACTERISTICS</b>						
Output Voltage High	$V_{OH}$	$R_L = 100k\Omega$ to Ground $-40^\circ C \leq T_A \leq +125^\circ C$	2.68	2.695		V
		$R_L = 10k\Omega$ to Ground $-40^\circ C \leq T_A \leq +125^\circ C$	2.68	2.695		V
		$R_L = 10k\Omega$ to Ground $-40^\circ C \leq T_A \leq +125^\circ C$	2.67	2.68		V
		$R_L = 10k\Omega$ to Ground $-40^\circ C \leq T_A \leq +125^\circ C$	2.67	2.675		V
Output Voltage Low	$V_{OL}$	$R_L = 100k\Omega$ to V+ $-40^\circ C \leq T_A \leq +125^\circ C$		1	10	mV
		$R_L = 10 k\Omega$ to V+ $-40^\circ C \leq T_A \leq +125^\circ C$		2	10	mV
		$R_L = 10 k\Omega$ to V+ $-40^\circ C \leq T_A \leq +125^\circ C$		10	20	mV
		$R_L = 10 k\Omega$ to V+ $-40^\circ C \leq T_A \leq +125^\circ C$		15	20	mV
Short Circuit Limit	$I_{SC}$	$-40^\circ C \leq T_A \leq +125^\circ C$	$\pm 10$	$\pm 15$		mA
Output Current	$I_O$	$-40^\circ C \leq T_A \leq +125^\circ C$		$\pm 10$		mA
		$-40^\circ C \leq T_A \leq +125^\circ C$		$\pm 5$		mA
<b>POWER SUPPLY</b>						
Power Supply Rejection Ratio	PSRR	$V_S = 2.7V$ to 5.5 V $-40^\circ C \leq T_A \leq +125^\circ C$	120	130		dB
		$-40^\circ C \leq T_A \leq +125^\circ C$	115	130		dB
Supply Current/Amplifier	$I_{SY}$	$V_O = 0V$ $-40^\circ C \leq T_A \leq +125^\circ C$		1.1	1.4	mA
		$-40^\circ C \leq T_A \leq +125^\circ C$		1.3	1.6	mA
<b>DYNAMIC PERFORMANCE</b>						
Slew Rate	SR	$R_L = 10 k\Omega$		1		V/ $\mu s$
Overload Recovery Time				0.05		ms
Gain Bandwidth Product	GBP			2		MHz
<b>NOISE PERFORMANCE</b>						
Voltage Noise	$e_{n p-p}$	0.1 to 10 Hz		0.75		$\mu V_{p-p}$
Voltage Noise Density	$e_n$	$f = 1 kHz$		33		nV/ $\sqrt{Hz}$
Current Noise Density	$i_n$	$f=10 Hz$		5		fA/ $\sqrt{Hz}$

# PRELIMINARY TECHNICAL DATA

## AD8628

### ABSOLUTE MAXIMUM RATINGS

Supply Voltage .....	+6V
Input Voltage.....	GND to $V_s + 0.3V$
Differential Input Voltage <sup>1</sup> .....	$\pm 5.0V$
Output Short-Circuit Duration to Gnd.....	Indefinite
Storage Temperature Range	
RT, R Package .....	-65°C to +150°C
Operating Temperature Range	
AD8628 .....	-40°C to +125°C
Junction Temperature Range	
RT, R Package .....	-65°C to +150°C
Lead Temperature Range (Soldering, 10 sec).....	+300°C

Package Type	$\theta_{JA}$ <sup>2</sup>	$\theta_{JC}$	Units
5-Pin SOT23 (RT)			°C/W
8-Pin SOIC (R)	158	43	°C/W

### NOTES

- <sup>1</sup> Differential input voltage is limited to  $\pm 5.0$  volts or the supply voltage, whichever is less.  
<sup>2</sup>  $\theta_{JA}$  is specified for the worst case conditions, i.e.,  $\theta_{JA}$  is specified for device in socket for P-DIP packages;  $\theta_{JA}$  is specified for device soldered in circuit board for SOIC and TSSOP packages.

### ORDERING GUIDE

Model	Temperature Range	Package Description	Package Option
AD8628ART	-40°C to +125°C	5-Pin SOT23	RT-5
AD8628AR	-40°C to +125°C	8-Pin SOIC	SO-8